



AA-T0022

# DIGITAL THERMOMETER

## Functions:

- Memory of the last measuring data, when open, display the last measuring date for 1.5 second then jump to normal display.
- Measuring and display low voltage: when voltage lower than 1.3v, LCD displays will show "LOW"
- Power saving: auto-off after 15minutes idle.
- Sensor error display: Display "LLL" when sensor open circuit or lower than measuring range; Display "HHH" when sensor short circuit or higher than measuring range.
- Can switch between °C and °F.

## Operation descriptions:

- On/Off : Press the key to turn on/off the thermometer.
- °C/°F: Press °C/°F button once to change the temperature unit.
- Open the battery cover by swirling anti-clockwise, replace the battery then close the battery cover tightly by swirling clockwise.
- Please take out battery if don't use it for a long time.

## Specifications:

Temperature Range	-50°C ~ 300°C / -58°F ~ 572°F
Distinguishing Rate	0.1°C between -19.9°C ~ 199.9°C, otherwise 1°C
Accuracy	±1°C (between ± 20°C ~ 80°C), otherwise ±2°C
Ambient Temperature	-10°C ~ +40°C
Battery	1pcs x 1.5V AG13 or LR44
Probe Size	125mm (L)

